

## Verhuur Audiophony MPX12 - 12 channels Mixer with Compressor, Effects and USB/ SD/BT Player

Model: HU-MPX12

Merk: Audiophony



12 channels Mixer with Compressor, Effects and USB/ SD/BT Player

### **Mono Channels**

Microphone inputs : Balanced

Frequency response : 10Hz  
30KHz, +/-3dB

THD (THD&N) : 0.03% @ +4dBu, 22Hz-20KHz A weighted

Compression : Gain: 0-9dB, Threshold: 20dB 5dB

S/N ratio : 115 dB

Line inputs : Balanced

Frequency response : 10Hz  
30KHz, +/-3dB

THD (THD&N) : 0.005% @ +4dBu, 22Hz-20KHz A weighted

Maximum gain : 75 dBu 75 dBu Mic input Master output

## **Stereo channels**

Line inputs : Balanced/Unbalanced

Frequency response : 10Hz  
55KHz, +/-3dB

THD (THD&N) : 0.005% @ +4dBu, 22Hz-20KHz A weighted

## **Impedances**

Microphone inputs: 1,4 K Ohms

Line inputs: 10 K Ohms

Other inputs: 10 K Ohms ou plus

Recording input: 1 K Ohms

Other outputs: 120 Ohms

## **Mono channels EQ**

High +/-15dB @ 12 KHz

Mid +/-15dB @ 2,5 KHz

Low +/-15dB @ 45 Hz

## **Stereo channels EQ**

High: +/-15dB @ 12 KHz

Low: +/-15dB @ 60 KHz

Multi-effect : 24-bit analog-to-digital converter, 16 programs

Power supply : AC100~240V 50/60 Hz

Size : (L x L x E) : 330 x 392 x 92 mm

Weight : 5,2 Kg

[User guide English Version](#)

[User guide Deutsche Version](#)

[User guide Versión en Español](#)

[User guide Nederlandse Versie](#)